

Model : SQP450 (S)

Standby Power (50Hz)	450KVA/360KW
Prime Power(50Hz)	400KVA/320KW

Standard Features

- Engine: Perkins 2206C-E13TAG3
- Charge Alternator: 24V
- Governer: Electronic
- Generator: Stamford HCI444E
- Single Bearing Alternator IP23
- Insulation Class H/H
- Genuine radiator with engine driven fan
- Skid and vibration isolators
- Dry type air filter
- Main line circuit breaker (Below 500KVA)
- 12V battery and cable
- User's manual



Weight And Dimensions

Genset	Dimensions(LxWxH)	Weight (KG)
Open type	3200mmx1206mmx1980mm	3069
Silent type	4500mmx1583mmx2200mm	4860

Generator Ratings

Voltage	Hz	Phase	Power Factor	Standby (KVA/KW)	Prime (KVA/KW)
400/230	50	3	0.8	450/360	400/320

Criterion

- Generator sets: GB/T2820-1997, ISO9001: 2008
- Alternator: BS5000, VDE0530, NEMA MG1-32, IEC34, CSAC22.2-100, AS1359
- Diesel Engine: ISO3046, DIN6271



Engine Data

• Manufacturer/Model	Perkins 2206C-E13TAG3
• No.of Cylinders	6
• Displacement	12.5L
• Bore and Stroke	130*157(mm)
• Compression ratio	16.3:1
• Rated RPM	1500rpm
• Max.standby power at rated 1500RPM	392KW
• Aspiration	Turbocharged air-air charge cooled
• Governor Type	Electronic
• Exhaust Gas Flow @Standby Rating	75.8m ³ /min
• Exhaust Temperature @Standby Rating	630°C
• Intake Air Flow@Standby Rating	27.4m ³ /min
• Fuel System	Mechanically actuated electronically controlled unit full injectors with full authority electronic control
• 100%(Prime Power) Load	85Liter/H
• Lubrication System Min. capacity	32.5L
• Total Coolant Capacity	51.4L

Alternator Data

• Manufacture/Type	Stamford/HCI444E
• Number of phase power	3
• Factor	0.8
• Pole Number	4
• Bearing Number	1
• Exciter Type	Brushless, self-excited
• Insulation Class	H/H
• Protection	IP23

Control Panel



- Auto Module Control Panel, usually adopt control module of UK Deepsea DSE 7320 or Equal, is the configuration for nobody on duty generators control, This kind of panel adopts auto module control system, with large LCD display to show the menu.
- Features: receive remote output signal from ATS and realize auto start and stop of generators.
- Auto Mains Failure controller, can realize further more can detect ATS and control directly.
- RS232 or 485 interface which can communicate with PC to realize remote operation.





- Automatic Parallel Control Panel usually adopting intelligent control module of UK Deepsea DSE8610 or equal, this new automatic parallel system is inserted and folded installed, no need the peripheral relay and logic circuit. The main switch adopts electronic breaker or frame breaker, combined together with the generator, which is very reliable. One generator, one panel. The panel can be used both for single genset working or Gensets Parallel working. This kind of panel also can be used to parallel generator when the capability of the power plant needs to be enlarged in the future.

Optional

Engine	Alternator	Fuel System	Control System
<ul style="list-style-type: none"> • Pre-heater 	<ul style="list-style-type: none"> • Anti Condensation Heater • Drop CT (For Paralleling) 	<ul style="list-style-type: none"> • Daily Fuel Tank • Water Separator 	<ul style="list-style-type: none"> • Remote Control Panel • Auto Transfer Switch (ATS) • Paralleling System • Electricity Output Cabinet

Others

- Rainproof Type
- Soundproof Type
- Trailer Type
- Container Type
- Spare Parts



Warranty



- Warranty is according to our standard conditions: 12 months or 1,200 running hours, subject to the earlier one. And what's more, Perkins gensets enjoy world-wide united Warranty from Perkins engine agency or service centre at the client's local side.
- Service and parts are available from Guangzhou Sanq Power Equipment Co.,Ltd or our distributors in your location.

