

Model : SQC150 (S)

Standby Power (50Hz)	150KVA/120KW
Prime Power(50Hz)	138KVA/110KW

Standard Features

- Engine: Cummins 6BTAA5.9-G2
- Charge Alternator: 24V
- Governer: Electronic
- Generator: Stamford UC1274E
- Single Bearing Alternator IP23
- Insulation Class H/H
- Genuine radiator with engine driven fan
- Skid and vibration isolators
- Dry type air filter
- Main line circuit breaker (Below 500KVA)
- 12V battery and cable
- User's manual



Weight And Dimensions

Genset	Dimensions(LxWxH)	Weight (KG)
Open type	2360mmx830mmx1334mm	1381
Silent type	3300mmx1150mmx1800mm	2168

Generator Ratings

Voltage	Hz	Phase	Power Factor	Standby (KVA/KW)	Prime (KVA/KW)
400/230	50	3	0.8	150/120	138/110

Criterion

- Generator sets: GB/T2820-1997, ISO9001: 2008
- Alternator: BS5000, VDE0530, NEMA MG1-32, IEC34, CSAC22.2-100, AS1359
- Diesel Engine: ISO3046, DIN6271



Engine Data

• Manufacturer/Model	DCEC Cummins 6BTAA5.9-G2
• No.of Cylinders	6
• Displacement	5.9L
• Bore and Stroke	102*120(mm)
• Compression ratio	17.3:1
• Rated RPM	1500rpm
• Max.standby power at rated 1500RPM	130KW
• Aspiration	Turbocharged and Charge Air Cooled
• Governor Type	GAC governor
• Exhaust Gas Flow @Standby Rating	328L/S
• Exhaust Temperature @Standby Rating	540°C
• Intake Air Flow@Standby Rating	120liter/s
• Fuel System	BYC PB/Electronic Governor
• 100%(Prime Power) Load	30Liter/H
• Lubrication System Min.	16.4L
• Total Coolant Capacity	10L

Alternator Data

• Manufacture/Type	Stamford/UCI274E
• Number of phase power	3
• Factor	0.8
• Pole Number	4
• Bearing Number	1
• Exciter Type	Brushless, self-excited
• Insulation Class	H/H
• Protection	IP23

Control Panel



- Auto Module Control Panel, usually adopt control module of UK Deepsea DSE 6020 or Equal, is the configuration for nobody on duty generators control, This kind of panel adopts auto module control system, with large LCD display to show the menu.
- Features: receive remote output signal from ATS and realize auto start and stop of generators.
- Auto Mains Failure controller, can realize further more can detect ATS and control directly.





- Automatic Parallel Control Panel usually adopting intelligent control module of UK Deepsea DSE8610 or equal, this new automatic parallel system is inserted and folded installed, no need the peripheral relay and logic circuit. The main switch adopts electronic breaker or frame breaker, combined together with the generator, which is very reliable. One generator, one panel. The panel can be used both for single genset working or Gensets Parallel working. This kind of panel also can be used to parallel generator when the capability of the power plant needs to be enlarged in the future.

Optional

Engine	Alternator	Fuel System	Control System
<ul style="list-style-type: none"> • Pre-heater 	<ul style="list-style-type: none"> • Anti Condensation Heater • Drop CT (For Paralleling) 	<ul style="list-style-type: none"> • Daily Fuel Tank • Water Separator 	<ul style="list-style-type: none"> • Remote Control Panel • Auto Transfer Switch (ATS) • Paralleling System • Electricity Output Cabinet

Others

- Rainproof Type
- Soundproof Type
- Trailer Type
- Container Type
- Spare Parts



Warranty

- Warranty is according to our standard conditions: 12 months or 1,200 running hours, subject to the earlier one. And what's more, Cummins gensets enjoy world-wide united Warranty from Cummins engine agency or service centre at the client's local side.
- Service and parts are available from Guangzhou Sanq Power Equipment Co.,Ltd or our distributors in your location.

